

JLG BOMLIFTE MED INDBYGGET FORBRÆNDINGSMOTOR 450AJ SERIE II GM3.0



MOTOR GM 3.0

Kapacitet: 4,25 liter

ANVEND

Normal

KLIMA

Moderat

PRODUKTANBEFALING 1

Kroontrak MTH 10W-30

Skift alle 3 måneder/ 150 timer

NAVREDUKTIONER BAG

Kapacitet: 0,7 liter

ANVEND

Normal

KLIMA

Moderat

PRODUKTANBEFALING 1

Gearlube GL-5 80W-90

PRODUKTANBEFALING 2

Unigear HS GL-3/GL-5 80W-90

Kontroller alle 3 måneder/ 150 timer, skift alle 24 måneder/ 1200 timer

NAVREDUKTIONER FOR

Kapacitet: 0,7 liter

ANVEND

Normal

KLIMA

Moderat

PRODUKTANBEFALING 1

Gearlube GL-5 80W-90

PRODUKTANBEFALING 2

Unigear HS GL-3/GL-5 80W-90

Kontroller alle 3 måneder/ 150 timer, skift alle 24 måneder/ 1200 timer

HYDRAULISK SYSTEM

ANVEND

Normal

KLIMA

Moderat

PRODUKTANBEFALING 1

Agrifluid Synth XHP Ultra

PRODUKTANBEFALING 2

Agrifluid HT-Plus

PRODUKTANBEFALING 3

Kroontrak MTH 10W-30

Skift alle 1200 timer/ 24 måneder

SMØREPUNKTER/NIPLER

ANVEND

Normal

KLIMA

Moderat

PRODUKTANBEFALING 1

Labora Grease

PRODUKTANBEFALING 2

Q5 MP Calcep Grease EP 2

PRODUKTANBEFALING 3

MP Lithep Grease EP 2

Kontroller alle 3 måneder/ 150 timer

JLG BOMLIFTE MED INDBYGGET FORBRÆNDINGSMOTOR 450AJ SERIE II GM3.0



KØLESYSTEM

ANVEND

Normal

KLIMA

Moderat

PRODUKTANBEFALING 1

Coolant -38 Organic NF

PRODUKTANBEFALING 2

Coolant -26

The data mentioned in this product information sheet is meant to enable the reader to orientate himself about the properties and possible applications of our products. Although this overview is composed with all possible care on the stated date, the compiler does not accept any liability for damages caused by incompleteness and/or inaccuracies in this information, especially when these are caused by obvious typing errors. The terms of delivery of the supplier apply to all product supplies. The reader is advised, especially for critical applications, to make the final product choice in consultation with the supplier. Due to continual product research and development, the information contained herein is subject to changes without notification.